

JWS120P

EVALUATION DATA

型式データ

DWG No. A181-53-01			
QA APPD	APPD	CHK	DWG
Murayama 3/Sep/99	P. J. H. 2 23/Aug/99	S. Kuroyama 23/Aug/99	T. Matsumoto 31/Aug/99

INDEX

1. 測定方法 Evaluation Method	PAGE
1.1 測定回路 Circuit used for determination	T-1~5
(1) 静特性 Steady state data	
(2) 通電ドリフト特性 Warm up voltage drift characteristics	
(3) 過電流保護特性 Over current protection (OCP) characteristics	
(4) 過電圧保護特性 Over voltage protection (OVP) characteristics	
(5) 出力立ち上がり特性 Output rise characteristics	
(6) 出力立ち下がり特性 Output fall characteristics	
(7) 過渡応答 (入力急変) 特性 Dynamic line response characteristics	
(8) 過渡応答 (負荷急変) 特性 Dynamic load response characteristics	
(9) 入力サージ電流 (突入電流) 特性 Inrush current characteristics	
(10) リーク電流特性 Leakage current characteristics	
(11) 出力リップル、ノイズ波形 Output ripple and noise waveform	
(12) EMI特性 Electro-Magnetic Interference characteristics	
1.2 使用測定機器 List of equipment used	T-6
2. 特性データ Characteristics	
2.1 静特性 Steady state data	
(1) 入力・負荷・温度変動	
Regulation - line and load, temperature drift	T-7
(2) 出力電圧・リップル電圧対入力電圧	
Output voltage and ripple voltage vs. input voltage	T-8
(3) 効率・入力電流対出力電流	
Efficiency and input current vs. output current	T-9
(4) 力率・入力電流対出力電流	
Power factor and input current vs. output current	T-10
2.2 通電ドリフト特性 Warm up voltage drift characteristics	T-11
2.3 過電流保護特性 Over current protection (OCP) characteristics	T-12
2.4 過電圧保護特性 Over voltage protection (OVP) characteristics	T-13
2.5 出力立ち上がり特性 Output rise characteristics	T-14~15
2.6 出力立ち下がり特性 Output fall characteristics	T-16~17
2.7 出力保持時間特性 Hold up time characteristics	T-18
2.8 過渡応答 (入力急変) 特性 Dynamic line response characteristics	T-19
2.9 過渡応答 (負荷急変) 特性 Dynamic load response characteristics	T-20~21
2.10 入力電圧瞬停特性 Response to brown out characteristics	T-22~23

2.11	入力サージ電流（突入電流）特性	Inrush current waveform	T-24～25
2.12	瞬停時突入電流特性	Inrush current characteristics	T-26
2.13	入力電流波形	Input current waveform	T-27
2.14	高調波成分	Input current harmonics	T-28
2.15	リーク電流特性	Leakage current characteristics	T-29～30
2.16	出力リップル、ノイズ波形	Output ripple and noise waveform	T-31～32
2.17	EMI特性	Electro-Magnetic Interference characteristics	T-33～35

使用記号 Terminology used

Definition


Vin	入力電圧	Input voltage
Vout	出力電圧	Output voltage
Iin	入力電流	Input current
Iout	出力電流	Output current
f	周波数	Frequency
Ta	周囲温度	Ambient temperature

1 . 1

測定回路
Circuit used for determination


(1) 静特性

Steady state data




(2) 通電ドリフト特性

Warm up voltage drift characteristics




(3) 過電流保護特性

Over current protection (O.C.P.) characteristics




(4) 過電圧保護特性

Over voltage protection (O.V.P.) characteristics



(5) 出力立ち上がり特性

Output rise characteristics




(6) 出力立ち下がり特性

Output fall characteristics

Same as output rise characteristics


(7) 過渡応答（入力急変）

Dynamic line response characteristics




(8) 過渡応答（負荷急変）特性

Dynamic load response characteristics




(9) 入力サージ電流（突入電流）特性

Inrush current characteristics



(10) リーク電流

Leakage current characteristics



NOTE : Leakage current measured through a 1kohm resistor.


Range used --- AC+DC (For YOKOGAWA TYPE 3226)

--- AC (For SIMPSON MODEL 229-2)


(11) 出力リップルノイズ

Output ripple noise

(a) Normal Mode



(b) Normal + Common Mode




(12) EMI 特性

Electro-Magnetic Interference characteristics


(a) 雜音端子電圧 (帰還ノイズ)

Conducted Emission Noise



(b) 雜音電界強度 (輻射ノイズ)

Radiated Emission Noise



1.2 使用測定機器 LIST OF EQUIPMENT USED

	EQUIPMENT USED	MANUFACTURER	MODEL NO.
1	OSCILLOSCOPE	HITACHI DENSHI	V-1100A
2	DIGITAL STORAGE OSCILLOSCOPE	TEKTRONIX	TDS540B
3	DIGITAL MULTIMETER	ADVANTEST	R6341A
4	DIGITAL POWER METER	YOKOGAWA ELECT.	WT110
5	SHUNT RESISTOR	YOKOGAWA ELECT.	
6	CURRENT PROBE/AMPLIFIER	TEKTRONIX	A6303/AM503
7	DYNAMIC DUMMY LOAD	TAKASAGO	
8	SLIDE REGULATOR	MATSUNAGA	SD-2625
9	CVCF	KIKUSUI	PCR4000L
10	LEAKAGE CURRENT METER	SIMPSON	229-2
11	LEAKAGE CURRENT METER	YOKOGAWA	TYPE3226
12	X-Y RECORDER	GRAPHTEC	WX3000-1
13	DYNAMIC DIP SIMULATOR	TAKAMISAWA CYBERNETICS	PSA-300
14	CONTROLLED TEMP. CHAMBER	TABAI ESPEC	PSL-2KPH-A
15	SPECTRUM ANALYZER	ROHDE & SCHWARZ	FSA
16	EMI TEST RECEIVER	ROHDE & SCHWARZ	ESHS10
17	EMI TEST RECEIVER	ROHDE & SCHWARZ	ESVS10
18	RF RELAY MATRIX	ROHDE & SCHWARZ	PSU
19	AMN	KYORITSU DENSHI	KNW-242
20	ANTENNA(BICONICAL ANTENNA)	SCHWARZBECK	BBA9106

2. 特性データ Characteristics

2.1 静特性 Steady state data

(1) 入力、負荷、温度変動 Regulation - line and load, temperature drift

24V

1. Regulation - line and load

condition Ta : 25°C

Iout \ Vin	85VAC	100VAC	200VAC	265VAC	line regulation	
0%	23.97V	23.97V	23.97V	23.97V	0mV	0.000%
50%	23.96V	23.96V	23.96V	23.96V	0mV	0.000%
100%	23.96V	23.96V	23.96V	23.96V	0mV	0.000%
load	10mV	10mV	10mV	10mV		
regulation	0.04%	0.04%	0.04%	0.04%		

2. Temperature drift

conditions Vin=100VAC

Io =100%

Ta	-10°C	+25°C	+50°C	temperature stability	
Vo	23.92V	23.96V	23.97V	50mV	0.17%

48V

1. Regulation - line and load

condition Ta : 25°C

Iout \ Vin	85VAC	100VAC	200VAC	265VAC	line regulation	
0%	48.03V	48.03V	48.03V	48.03V	0mV	0.000%
50%	48.01V	48.01V	48.01V	48.01V	0mV	0.000%
100%	48.01V	48.01V	48.01V	48.01V	0mV	0.000%
load	20mV	20mV	20mV	20mV		
regulation	0.04%	0.04%	0.04%	0.04%		

2. Temperature drift



conditions Vin=100VAC

Io =100%

Ta	-10°C	+25°C	+50°C	temperature stability	
Vo	48.01V	48.01V	47.99V	20mV	0.04%

2.1 (2) 出力電圧、リップル電圧対入力電圧
 Output voltage and Ripple voltage v.s. Input voltage

Conditions Iout : 100%
 Ta : -10°C
 : 25°C - - -
 : 50°C ———




2.1 (3) 効率、入力電流対出力電流


Efficiency and Input current v.s. Output current

Conditions Vin : 85VAC -----
 : 100VAC -----
 : 200VAC ————
 : 265VAC -----
 Ta : 25°C

24V





48V



2.1 (4) 力率、入力電流対出力電流

Power factor and Input current v.s. Output current

Conditions

Vin : 85VAC -----
: 100VAC -----
: 200VAC ————
: 265VAC -----
Ta : 25°C**24V****48V**



2.2 通電ドリフト特性

Warm up voltage drift characteristics

Conditions Vin : 100VAC

Iout : 100%



Ta : 25°C

24V**48V**

2.3 過電流保護特性

Over current protection (OCP) characteristics



Conditions Ta : -10°C
: 25°C - - -
: 50°C ———
Vin : 85-265VAC

24V**48V**

2.4 過電圧保護特性



Over voltage protection (OVP) characteristics

Conditions Vin : 100VAC
 Iout : 0%
 Ta : 25°C





2.5 出力立ち上がり特性
Output rise characteristics

Conditions Vin : 85VAC (A)
 : 100VAC (B)
 : 200VAC (C)
 : 265VAC (D)
Iout : 0%
Ta : 25°C

24V**48V**



2.5 出力立ち上がり特性
Output rise characteristics

Conditions Vin : 85VAC (A)
 : 100VAC (B)
 : 200VAC (C)
 : 265VAC (D)
Iout : 100%
Ta : 25°C





2.6 出力立ち下がり特性
Output fall characteristics

Conditions Vin : 85VAC (A)
 : 100VAC (B)
 : 200VAC (C)
 : 265VAC (D)
Iout : 0%
Ta : 25°C



2.6 出力立ち下がり特性
Output fall characteristics

Conditions Vin : 85VAC (A)
 : 100VAC (B)
 : 200VAC (C)
 : 265VAC (D)
Iout : 100%
Ta : 25°C





2.7 出力保持時間特性



Hold up time characteristics

Conditions Vin : 100VAC

: 200VAC

Ta : 25°C

24V**48V**



2.8 過渡応答（入力急変）特性
Dynamic line response characteristicsConditions Vin : 85VAC \leftrightarrow 132VAC(A)
170VAC \leftrightarrow 265VAC(B)
Iout : 100%
Ta : 25°C

2.9 過渡応答（負荷急変）特性
Dynamic load response characteristics



Conditions Vin : 100VAC
Ta : 25°C

24V

f=100Hz







f=1kHz



2.9 過渡応答（負荷急変）特性
Dynamic load response characteristics

Conditions Vin : 100VAC
Ta : 25°C

48V

f=100Hzf=1kHz

2.10 入力電圧瞬停特性



Response to brown out characteristics

Conditions

Vin : 100VAC

Iout : 100%

Ta : 25°C



2.10 入力電圧瞬停特性



Response to brown out characteristics



Conditions



Vin : 200VAC

Iout : 100%

Ta : 25°C



2.11 入力サージ電流（突入電流）特性
Inrush current waveformConditions Vin : 100VAC
 Iout : 100%
 Ta : 25°C**24V**Switch on phase angle
of input AC voltage
 $\phi = 0^\circ$ Switch on phase angle
of input AC voltage
 $\phi = 90^\circ$ 


2.11 入力サージ電流（突入電流）特性
Inrush current waveformConditions
Vin : 200VAC
Iout : 100%
Ta : 25°C**24V**Switch on phase angle
of input AC voltage
 $\phi = 0^\circ$ Switch on phase angle
of input AC voltage
 $\phi = 90^\circ$ 

2.12 瞬停時突入電流特性
Inrush current characteristics


Conditions Iout : 0% -----
: 50% - - - - -
: 100% —————
Ta : 25°C

24V

Vin : 100VAC




Vin : 200VAC




2.13 入力電流波形
Input current waveform

24V



Conditions Vin : 100VAC
 Iout : 100%
 Ta : 25°C



Conditions Vin : 200VAC
 Iout : 100%
 Ta : 25°C



2.14 高調波成分
Input current harmonics



2.15 リーク電流特性

Leakage current characteristics

Conditions Iout : 0% -----


: 100% ———

Ta : 25°C


f : 50Hz

Equipment used : MODEL 229-2 (Simpson)

24V



48V



2.15 リーク電流特性

Leakage current characteristics

Conditions Iout : 0% -----


: 100% ———

Ta : 25°C


f : 50Hz

Equipment used : TYPE3226 (YOKOGAWA)

24V



48V




2.16 出力リップル、ノイズ波形
Output ripple and noise waveform


Conditions Vin : 100VAC
Iout : 100%
Ta : 25°C

NORMAL MODE

24V



48V




2.16 出力リップル、ノイズ波形
Output ripple and noise waveform

Conditions Vin : 100VAC
Iout : 100%
Ta : 25°C


NORMAL + COMMON MODE

24V



← V_{out}

48V



← V_{out}

2.17 EMI 特性


Electro-Magnetic Interference characteristics

雜音端子電圧

Conducted Emission

24V


Conditions Vin : 100VAC
 Iout : 100%



Phase : N

48V

Conditions Vin : 100VAC
 Iout : 100%



Phase : N

EN55011-A, EN55022-Aの限界値はVCCI class Aの限界値と同じ
 Limits of EN55011-A, EN55022-A are same as its VCCI class A.

2.17 E M I 特性

Electro-Magnetic Interference characteristics

雜音電界強度

Radiated Emission


Conditions Vin : 230VAC

Iout : 100%

24V


HORIZONTAL:

Point A (147.9MHz)		
Ref.	VCCI-Limit (dBuV/m)	Measure (dBuV/m)
QP	50.0	41.3



VERTICAL:

Point B (149.0MHz)		
Ref.	VCCI-Limit (dBuV/m)	Measure (dBuV/m)
QP	50.0	39.5



EN55011-A, EN55022-Aの限界値はVCCI class Aの限界値と同じ

Limits of EN55011-A, EN55022-A are same as its VCCI class A.

2.17 E M I 特性

Electro-Magnetic Interference characteristics

雜音電界強度

Radiated Emission


Conditions Vin : 230VAC

Iout : 100%

48V


HORIZONTAL:

Point A (149.9MHz)		
Ref.	VCCI-Limit (dBuV/m)	Measure (dBuV/m)
QP	50.0	40.4



VERTICAL:

Point B (148.4MHz)		
Ref.	VCCI-Limit (dBuV/m)	Measure (dBuV/m)
QP	50.0	41.4



EN55011-A, EN55022-Aの限界値はVCCI class Aの限界値と同じ

Limits of EN55011-A, EN55022-A are same as its VCCI class A.



NEMIC-LAMBDA